

MODULAR UNINTERRUPTIBLE POWER SUPPLY SYSTEM AND CONTROL METHOD THEREOF

BACKGROUND OF THE INVENTION

1. Field of the Invention

The present invention relates to a modular uninterruptible power supply system and control method thereof, in particular to a system of parallel UPS modules all with full uninterruptible power supply capabilities, and identical control logic and functional capabilities for initiating role detection dynamically and electing a virtual master through the arbitration process to control the parallel operation of UPS modules. The system design has incorporated the characteristics of both centralized control and distributed processing by dispensing with a dedicated control module, and is able to operate with one or more UPS modules in parallel, providing fault tolerance and maximum redundancy, and reducing the risks of system-level single point failure to minimum possibility to the emergent and sensitive load.

2. Description of Related Arts

Computers and networking have become essential tools for enhancing the economic and technological development in many countries. To keep the operation of computers and networks working in normal operating conditions, there has to be a continuous supply of electrical power. As is commonly known, high-tech systems cannot tolerate even a brief loss of power, which could cause severe data loss for the data processing equipment and breakdown of the data communication systems. To prevent such accidents, companies and individual users see the benefits of having an uninterruptible power supply to protect their

1 installation and the operation results. Therefore, the demand for the
2 uninterruptible power supply is increasing steadily.

3 An uninterruptible power supply receives AC and DC input power and
4 provides an AC output power to a load. In general, the AC input power is
5 generally provided by the utility companies or the power generators, whilst the
6 DC power is generally supplied by the batteries. The AC output power provides
7 the necessary electrical power for driving the electrical equipment, and the
8 controller controls the systems. If the sensitive equipment is installed with a UPS,
9 when the main line is failed, the power source will be automatically switched to
10 the secondary source. The DC power from the battery is used to maintain a
11 continuous power supply to the load.

12 A UPS offers line filtering and power regulation for a main line in
13 normal conditions and a secondary power source when the supply from the main
14 line is interrupted. When the AC output is normal, the system input of the UPS is
15 connected to a filter for filtering out line noises, and then through an AC/DC
16 converter to an DC bus for saving the DC power, and then the DC bus is
17 connected to a DC/AC inverter through an optional output filter to provide the
18 necessary power to the load.

19 When the AC input is interrupted, the DC power will be drawn from the
20 secondary source passing through a DC/DC converter to the DC bus replacing
21 the AC input by converting DC input power to DC Bus, and then further through
22 a DC/AC inverter generating AC power connected to the load. This type of UPS
23 usually also has a charger if the secondary DC source are batteries to recharge the
24 batteries once the main line is returned to the normal supply conditions.

1 The conventional structure of a UPS is only able to provide a continuous
2 supply of electrical power for the operating loads, however, it cannot satisfy the
3 continuously increasing requirements of the load. If the load capacity is varied or
4 increased, the original UPS may not be able to handle the new demands. There
5 may also be stringent demand for fault tolerance, which would be beyond the
6 provision of the conventional UPS. The answer to these problems is a modular
7 UPS system. The modular system design has the advantages of scalability and
8 redundancy, which are becoming a trend for the future.

9 Increasing the number of UPS units to satisfy the expansion and
10 replacement needs will encounter a problem in parallel operation. The control
11 technology has to take care of the cross conduction current from UPS modules
12 with different output power as they are connected in parallel. Excessive cross
13 conduction current will lead to system breakdown. The related control
14 technology for a power supply system has been widely discussed in the academic
15 and industrial fields and they are considered key issues for a reliable parallel
16 system.

17 Modular UPS for parallel operation can be generally classified basing on
18 their control methods. The first class of modular UPS systems are built with the
19 wire bus control, and the second class of UPS systems employ the wireless
20 control. Both designs have been sufficiently disclosed by prior arts. In one case a
21 parallel redundant power supply system is built by using the AC output voltage
22 level to coordinate load sharing, and in another case the load balancing and the
23 reduction in cross conduction current are achieved without the need for common
24 control circuitry between the parallel inverters.

1 For implementations using the wire bus control, a sync clock signal is
2 used to synchronize the output voltage phase across all UPS modules, and with
3 inter-unit signaling of loading status between UPS modules load balancing can
4 be achieved, but the results are not satisfactory. The wire bus control method for
5 controlling parallel operation could cause system-level single point failure.

6 In one prior art US Pat. 6,121,695, each UPS module is considered as an
7 independent UPS function, but when they are put into a housing for parallel
8 connection each UPS module needs to be respectively connected to a controller
9 for controlling parallel operation. In addition, the DC bus is interconnected by all
10 parallel UPS modules. If the DC bus is damaged, the whole system will not be
11 able to operate, representing a typical case of the system-level single point
12 failure. The proposed UPS modules therefore are not truly independent operation
13 units. Besides, since the batteries of the UPS modules are not connected in
14 parallel, the unit discharging time for different batteries may not be the same due
15 to their inherent discharging characteristics, and the discharging time, in this
16 case, cannot be extended by adding optional batteries. A majority rule decides for
17 all UPS modules whether to switch to main line or battery output. The control
18 signals exchanged between individual UPS modules are decided by an average
19 impedance value, and the configuration of UPS modules cannot be modified by
20 external means. There is no controller to coordinate the system, even the situation
21 is very emergency, the system is still just judged by a so-called "majority rule"
22 regardless of the possibility of system-level single-point failure. Thus the
23 important and sensitive load is under a dangerous condition.

24 Also, in still another prior art US Pat. 6,201,319, a main intelligence

1 module (MIM) is employed for managing the power modules, and a redundant
2 intelligence module (RIM) for the redundant control. However, these idling units
3 in normal conditions will create unnecessary waste of system resources. The
4 system is only equipped with power modules and external controllers. The power
5 module is not designed with full uninterruptible power supply capabilities, some
6 of the important characteristics are put in MIM, and only some of them are
7 redundant in RIM. For example, the important operation data such as input
8 voltage, frequency, output voltage, frequency, and current are centrally collected
9 and stored in the MIM. The system could only enhance the redundancy of power
10 module thus avoid the module-level failure. Moreover, the connected wired
11 between the MIM or RIM and the power modules and some signals only
12 designed in MIM are not redundant, if they are inoperative, the result will turn to
13 be a system-level single point failure.

14 Lastly, still another prior art US Pat.6,396,170 uses a virtual controller
15 model. Although it could avoid the loss of RIM reducing the risks of a system-
16 level single point failure, the system simultaneously creates a master and a vice
17 master in two separate UPS modules. If there is only one UPS module in the
18 system, then the system will not be able to function. Moreover, the use of a
19 common sync line also increases the risks of system-level single point failure. If
20 this sync line is defeated, the total system is shut-down. Also, the proposed
21 system architecture for the redundancy management (RMB) would require a
22 complicated procedure to determine the direction of input and output, and to elect
23 the virtual master or vice virtual master. Also, the sync line needs a high level
24 system interrupt and a fast response management model, which wastes large

resources on that, could use alternative method to get the same result. If any UPS module is down or experiences interfacing problems, the unit cannot initiate a mode switch for itself, and instead the master will order all UPS modules to switch to a default mode leading to even more serious problems for the system.

From the foregoing, some of the above-described examples of parallel power supply systems can only use the redundant control method to avoid the module-level failure, but they cannot obviate the risks of system-level single point failure; some of the examples though try to enhance the redundancy in system-level failure, but they use very complicated method, and waste lots of control resources, thus result another kind of system-level failure. The conventional methods therefore cannot provide excellent fault tolerance in parallel operation. A more advanced solution is needed for controlling the synchronous operation of UPS modules connected in parallel.

SUMMARY OF THE INVENTION

The main object of the present invention is to provide a method for controlling parallel operation of a modular uninterruptible power supply (UPS) system, with units possessing full uninterruptible power supply capabilities and identical control logic and functional capabilities for self-initiated role detection, master arbitration and parallel processing, so as to enhance fault tolerance and redundancy management.

To this end, each UPS module is adapted to perform in the following functional modes:

Self-initiated role detection: this is mainly used for determining the functional role of the unit after the arbitration processes as a new entrant, virtual

1 master or virtual slave.

2 New entrant operation mode: it first searches for a virtual master in the
3 parallel UPS system. If the virtual master exists, it enters a wait for the virtual
4 master to issue a call-slave command, and from which the local UPS module will
5 switch itself over to the slave operation mode, but if the virtual master does not
6 exist, it will initiate the master arbitration for electing a virtual master;

7 Master operation mode: it sequentially checks the status of new entrants
8 and virtual slave in the system, and then requests response from the existing
9 virtual slaves, and collects their operation data for controlling the parallel
10 operation; and

11 Slave operation mode: it first checks if there is a virtual master in the
12 UPS system, if it does not exist, it will change itself to become a new entrant, and
13 then enter into the arbitration for new virtual master.

14 Using the above arbitration scheme, there will be only one virtual master
15 in existence in the system at any given time, but when the virtual master is failed
16 or inoperative in the network, other new entrants and virtual slaves will sense the
17 loss of the virtual master, and they will change themselves from the virtual slaves
18 to a new entrant mode to arbitrate for a new master through the arbitration
19 process. This arbitration scheme participated by all UPS modules is capable to
20 enhance the system redundancy and enhance system reliability.

21 The above UPS module, in accordance with the invention, further
22 possesses a synchronous switching mode, such that when the virtual master
23 detects that the system needs to be switched all at one point, it broadcasts a switch
24 command to all parallel UPS modules requesting the same action by all UPS

1 modules when the preset point is reached.

2 The above UPS module, in accordance with the invention, further
3 possesses an optional wireless control mode. When the synchronous control line
4 between the UPS modules experiences communication problem, the affected
5 UPS modules can decide to switch to the wireless control of parallel operation.

6 The above-mentioned wireless control of parallel operation is
7 implemented using a droop method, whereby respective UPS module collects
8 data from the AC output to determine their active power and reactive power
9 components, and then controls the resulting output phase and amplitude to
10 regulate the output frequency and voltage to achieve load balancing. Respective
11 UPS module may decide to shut down if internal problems develop.

12 The secondary object of the present invention is to provide a parallel
13 power supply system with fault tolerance.

14 To this end, the system contains one or more UPS modules in parallel
15 connection, and respective UPS module is built in with a microcontroller that is
16 capable of performing parallel processing, and inter-unit signaling between all
17 parallel UPS modules. The AC input, DC input, and AC output are connected in
18 parallel with other UPS modules for controlling the parallel operation. Through a
19 parallel control bus (PCB) connecting all parallel UPS modules, thus all parallel
20 UPS modules can exchange operational data by inter-unit signaling for load
21 balancing.

22 A typical UPS module contains an input filter, an AC/DC converter, a
23 DC bus, a DC/AC inverter, a DC/DC converter connected between the DC input
24 and DC bus, an optional charger, a power supply and a unit controller, wherein

1 the power supply is to provide the power to operate the internal components in
2 the UPS module; the unit controller is to control the operation of the local unit
3 and coordinate the parallel operation of the UPS modules through the control
4 bus.

5 The unit controller of respective UPS module is to control all functions
6 of the local UPS module and the mode transition. The unit controller is built in
7 with a digital signal processor (DSP) responsible for receiving and processing the
8 input and output voltage signals and signals passed back from the frequency
9 detection circuit, and signals returned by cross current detection circuit and load
10 current detection circuit.

11 The parallel control bus is used for controlling the parallel operation of
12 all UPS modules, which is composed of a photo-coupled bi-directional control
13 line, a communication bus, and an analog signal synthesis line. In the photo-
14 coupled bi-directional control line, one wire is used for configuring the virtual
15 master. For example, if the virtual master is not in existence, the line shows high
16 potential; otherwise it shows low potential. There is a sync clock line used for
17 synchronizing the output phase of all UPS modules. The analog signal synthesis
18 line is used for synthesizing the output current from all UPS modules.

19 The unit controller further includes general-use I/O functions, A/D
20 conversion functions and capabilities. The signal processor is capable of using
21 the feedback data from the DC bus voltage, AC output voltage, and cross
22 conduction current from the inverters to control the AC output voltage and
23 current to meet the load requirements.

24 The unit controller also provides power output calculation, as a safety

measure, to protect the load, and the detection of cross conduction current derived between the inverters in parallel operation.

BRIEF DESCRIPTION OF THE DRAWINGS

Fig. 1 is a block diagram of the overall architecture of the parallel power supply system in accordance with the present invention;

Fig. 2 is a block diagram of a typical UPS module;

Fig. 3 is a block diagram of a typical controller built in a UPS module;

Fig. 4 is a schematic circuit diagram of photo-coupled bi-directional communication bus in the controller;

Fig. 5 is schematic diagram of the analog signal synthesis line in the parallel power supply system;

Fig. 6 is a flow chart depicting the procedures for the self-initiated role detection mode for a UPS module;

Fig. 7 is a flow chart of the procedures for configuring a new entrant, including the virtual master arbitration process;

Fig. 8 is a flow chart of the procedures for configuring a virtual slave;

Fig. 9 is a flow chart of the first part of procedures for configuring a virtual master;

Fig. 10 is a flow chart of the second part of procedures for configuring a virtual master;

Fig. 11 is a diagram of an implementation of the wireless control of parallel operation for UPS modules in parallel with inductors respectively coupled to the output of the inverters; and

Fig. 12 is a flow chart for determining whether to use wire bus control or

1 wireless control of parallel operation.

2 DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

3 The present invention provides a modular uninterruptible power supply
4 (UPS) system (100) containing one or more UPS modules (10) connected in
5 parallel structure, as shown in Fig. 1. Each UPS module (10) has a unit controller
6 (17) for controlling multi-mode switching and parallel operation with other UPS
7 modules by connecting AC input, DC input and AC output in parallel with other
8 UPS modules (10). A parallel control bus (PCB) is used for inter-unit signaling
9 for exchanging operational data with unit controllers (17 of other UPS modules
10 (10) for coordinating the parallel operation.

11 Each UPS module in the power supply system possesses identical
12 control logic and functional capabilities for self-initiated role detection, master
13 arbitration, parallel processing. Each UPS module is able to support the self-
14 initiated role detection mode, new entrant mode, virtual master mode, and virtual
15 slave mode.

16 The procedures for operating the UPS module in the self-initiated role
17 detection mode are illustrated in Fig. 6, covered by steps (611)-(615). When first
18 started, the UPS module (10) has to determine if the unit should be a virtual
19 master, virtual slave or a new entrant by taking part in arbitration, and then
20 configures for the confirmed role accordingly.

21 The procedures for configuring the UPS module in the new entrant mode
22 are illustrated in Fig. 7. The program covers a master arbitration and single-unit
23 operation mechanism. For a UPS module (10) being added to the power supply
24 system (100), before confirming the role setting, the new UPS module is

1 initialized as new entrant. The new UPS module first checks if a virtual master
2 exists in the power supply system (711). If the virtual master is in existence, it
3 will wait for the virtual master to issue a call-slave command (712), which is a
4 routine check effected by an interrupt routine.

5 After receiving the call command from the virtual master, the new UPS
6 module configures itself as a virtual slave (713), and terminates the checking
7 process. If the call command doesn't come till the end of the interrupt routine, the
8 new UPS module will terminate the checking process and directly enter into a
9 wait for the call command from the virtual master. On the other hand, if the new
10 UPS module detects that the virtual master does not exist, that means there are
11 one or more UPS modules paralleled in operation. The new UPS module is
12 assigned a priority to arbitrate in the master arbitration (714). The new UPS
13 module then broadcasts the manufacturer's ID code continuously to other
14 parallel UPS modules to arbitrate for the virtual master (715) and then checks the
15 returned data if it contains the same content as the one issued before. In the
16 present embodiment, the system makes use of the hardware and software
17 characteristics of the control area network (CAN) for transmitting signals.
18 Supposing two or more UPS modules in the system simultaneously send out
19 messages containing an ID code to arbitrate for the virtual master, the one with
20 low potential will win the arbitration, and will receive the original message
21 containing its own ID, whilst other UPS modules will be configured to be the
22 virtual slave. If there is only one UPS module in operation, in that case it will not
23 be able to receive the own message echoed back, but after a predetermined time
24 of arbitration is over, and no one asserts to be the master, it will directly configure

1 to be the virtual master (716-719), that means there is only one UPS module
2 operating in the system (719).

3 In the master-arbitration process, it is only necessary to identify the ID
4 code without adding or multiplying any calculating time base, thus the actual
5 time needed for virtual master-arbitration time would only take 1.5 ms, as in the
6 present embodiment, even taking the battery operation mode into consideration
7 the arbitrating time would take no longer than 3.0 ms. Having the slew rate
8 appropriately controlled, the arbitrating process will not affect the AC output.
9 However, this is a fast way to initialize the system and to pick a virtual master
10 among the peers without wasting too many CPU resources.

11 In Fig. 8, the procedures for configuring the UPS as the virtual slave are
12 illustrated. The UPS module configured as a virtual slave first checks if a virtual
13 master is in existence (811). If for some reason the virtual master does not exist,
14 the same UPS module will immediately changes itself to become a new entrant
15 (812), and arbitrate for a new virtual master; otherwise, that means the virtual
16 master already exists, so it will enter a wait for the call command from the virtual
17 master and then will make a response (813) accordingly.

18 In Fig. 9, the flow chart for configuring the UPS module as a virtual
19 master is illustrated. A UPS module configured as the virtual master first checks
20 if any new entrant is added to the system (911); if this is true, it will then
21 determine if the number of virtual slaves in the current system is less than the
22 predetermined number (912). If this is true, the newly added UPS module will be
23 assigned to be the virtual slave (913), but if the number of existing virtual slaves
24 is greater than the predetermined number, the new entrant will be rejected by

1 ignoring its requests (914). This situation will happen only when the system
2 reaches the predetermined number that the system could take no more.

3 After having finished checking for new entrants, the virtual master
4 checks the current status of virtual slaves (915) by sequentially inquiring all
5 virtual slaves (916). If a virtual slave gives a response (917), that means the
6 virtual slave is in existence; otherwise, the virtual master will try once more with
7 an inquiry (918) trying to confirm if the virtual slave has been removed (919).
8 The UPS module then it checks the priority assigned and checks if there is more
9 than one virtual master (920) in existence. The former action is to check if the
10 virtual master for some reasons has switched over to the battery mode, while
11 some virtual slaves in the system are still operating in the power mains mode. If
12 that is true, the virtual master configures itself to be a new entrant and reinitiates
13 the master arbitration (921), such that one of the UPS modules in the power
14 mains mode will be able to become the new virtual master. The latter action is
15 necessary to prevent abnormal conditions from developing in the system, when
16 all the virtual slaves have finished with their responses (922), the program will be
17 terminated.

18 Besides the functional modes described above, the UPS module (10) is
19 built in with the capability of synchronous switching mode. The detailed flow
20 chart is shown in Fig. 10. The virtual master first checks if the system needs to be
21 switched over all at once, and prepares itself for such switching (411), then the
22 virtual master broadcasts synchronous switching commands received by itself,
23 all virtual slaves and all new entrants (412), and then it will perform synchronous
24 switching mode at a preset point (413), which generally refers to the zero

1 crossing point of output voltage for triggering the synchronous switching.

2 The so-called synchronous switching in the present context can be
3 subdivided into emergency and non-emergency cases. The decision to use either
4 case rests in the virtual master, or it could be decided by individual UPS modules.
5 The emergency case generally refers to a situation of bypass due to overload.
6 When the virtual master determines that the system approaches overload, and the
7 main line operates in the normal range, the system decides to switch all UPS
8 modules in the system from the inverter output to the bypass output all at once. In
9 the other hand, for the non-emergency case of the present embodiment, if the
10 switch mechanism is implemented within a double-conversion structure,
11 whereby the switching between power main and battery will not cause power
12 interruption for the load. For the system, it would be more ideal if the switching
13 decision can be made at the unit level without affecting other UPS modules,
14 which at that time may be in a different situation. Supposing part of a UPS
15 module is inoperative, the virtual master responds by switching all UPS modules
16 at once, therefore this action will result in more disorders for the UPS system.

17 The UPS modules in the system are further provided with an optional
18 wireless control mode. If it is found that the wire-control bus is not functioning
19 normally, the UPS module can decide to switch to wireless control to maintain
20 the parallel operation. The general concept of wireless control is depicted in Fig.
21 11. The output of the inverter is coupled with an inductor in series. The output
22 voltage and frequency can be regulated by appropriate control of inductance
23 therein. The required voltage and frequency difference between successive
24 voltage signals can be computed for determining the active power and reactive

1 power components, using the formulae given below:

$$P_i = \frac{V_i V_o}{X_{s1}} \sin \delta_i, \quad i = 1, 2, \dots, n$$
$$Q_i = \frac{V_i V_o \cos \delta_i - V_o^2}{X_{s1}}, \quad i = 1, 2, \dots, n$$

3 Where δ represents the adjacent angle between V_0 and V_1 .

4 From the above formulation, it can be found that active power is related
5 to the output phase angle, and reactive power to the output amplitude. It is
6 therefore possible to develop a control model for controlling the phase and
7 amplitude of inverter output by an appropriate means, using the following
8 relationship.

$$\omega_i = \omega_{0,i} - k_1 \cdot P_i, \quad i = 1, 2, \dots, n$$
$$V_i = V_{0,i} - k_2 \cdot Q_i, \quad i = 1, 2, \dots, n$$

10 The above wireless control of parallel operation by the droop method is
11 to use the feedback of the active and reactive power from the AC output of the
12 UPS module to adjust the phase angle and the voltage amplitude of the AC output
13 can be controlled by a phase-locked and amplitude-control loop. The control
14 process in wireless mode is shown in Fig. 12.

15 Under the mode of wireless control of parallel connection, the UPS
16 module first checks the parallel control bus if it is in normal condition (511),
17 especially the master configuring line, sync clock line and/or analog signal
18 synthesis line. If they are in normal conditions, the bus control mode will be
19 maintained for the parallel connection and the procedures will be terminated
20 (512). If the parallel control bus is found abnormal, the system will be switched
21 over to the wireless control of parallel connection (513). It should be noted at this
22 point the system still relies on the communication bus for electing a virtual

1 master, which is to facilitate data display and manual control to switch to the
2 bypass mode. The respective UPS module checks if the amplitude and frequency
3 of AC input signals are within the normal range (514); if this is true, the output
4 voltage will be phase locked to the AC input (515). The system then checks if an
5 abnormal condition develops inside the UPS module (516). The system then
6 proceeds to check if the communication bus is normal (517). If this is true, the
7 system is capable to switch to the bypass under certain situations (518) and all
8 procedures will be terminated. In the program, if the amplitude and/or frequency
9 of AC input are not within the normal range, the output will not be phase locked
10 to the input, and next it will check if an abnormal condition develops in the UPS
11 module (519). Regardless of whether the communication bus is normal or not, it
12 will not be able to switch to the bypass, and the UPS module will be shutdown
13 (520). In another situation, if the amplitude and/or frequency of AC input are
14 both within the normal range, but the communication bus is abnormal, it is
15 necessary to confirm if an abnormal condition develops in the UPS module,
16 which then leads to unit shutdown.

17 According to the above-mentioned method, the present invention
18 employs a dynamic process to elect a virtual master among the UPS modules,
19 which is responsible for controlling the parallel operation of UPS modules. In
20 case that the communication bus is inoperative, the system further provides a
21 way for switching to wireless control of parallel operation. This special feature is
22 unparalleled in other control techniques. Equipped with the wire-bus control for
23 the normal bus conditions and the wireless control for the abnormal bus
24 conditions, the overall reliability of the UPS system is substantially enhanced.

1 From the present invention, the preferred embodiment emphasizes a kind
2 of hybrid central control method, utilizing the spirits of the distributed and
3 central control method. This design makes the system more reliable than general
4 full distributed or full central control design. First, the redundancy of the system
5 is the number of the system, much better than only use the main external
6 controller and the redundant external controller, which redundancy is only two.
7 Second, in the present invention, no important control circuit is placed on so-
8 called external controller, which may cause the system-level single point failure,
9 and the reliability and fault tolerance is great and significantly enhanced. Third,
10 there are only one virtual master and virtual slaves in the steady-state system;
11 there is no need for so-called virtual vice-master, so only one UPS module is in
12 operation at any given time, and thus the system is provided with better
13 flexibility. Fourth, in this invention, better resources arrangement, and
14 wire/wireless bus is both equipped to enhance the reliability and availability.
15 From these mentioned characteristics, this invention discloses a superior control
16 method, which improves the redundancy, fault tolerance, and flexibility of the
17 prior design and similar type power supply.

18 The basic architecture of the power supply system (100) will be
19 described as Fig.1, comprising:

20 one or more battery units (101) for extending the discharging time;
21 a manual bypass switch (102) for maintenance and repair use;
22 a display and communication unit (103) for providing meaningful data to
23 users with regard to the internal operation and for monitoring the software
24 programs;

1 an optional charger (104) for charging the battery; and
2 an optional output transformer (not shown in diagram) for changing the
3 output voltage.

4 In the present embodiment, the output of the respective UPS module is
5 connected in parallel, which allows the load capacity to be increased and
6 provides the necessary system redundancy. It is possible to couple an isolation
7 transformer (not shown) to the AC output bus, which is mainly used for
8 decreasing the output voltage for low-voltage applications, such that many
9 electrical devices and harnesses will be able to reduced to match the power
10 requirements.

11 The AC input of the respective UPS module, as in the preferred
12 embodiment, is adapted to receive an AC input with a plurality of phases,
13 allowing expansion to suit larger power requirements. The UPS module (10) can
14 be connected by a plurality of wires and switches, such that the AC input with
15 one or more phase can be adapted to use the same UPS module.

16 The DC input of the respective UPS module, as in the preferred
17 embodiment, comes from one or more internally installed batteries (101) or
18 external batteries (105), The number of batteries can be controlled to match the
19 unit discharging time required by the system. If the discharging time does not
20 need to be extended, the batteries are not required to be connected in parallel,
21 without affecting the output from the parallel power supply system. In the
22 preferred embodiment, the AC inputs of all UPS modules are connected in
23 parallel to an external battery (105) for extending the discharging time.

24 The display and communication unit (103) is to communicate with the

1 elected virtual master, and for displaying meaningful information with respect to
2 the control system through an LCD or LED monitor, and the display and
3 communication unit (103) also act as an interface between the system and
4 external devices through RS232, RS485 or SNMP to facilitate system
5 reconfiguration or remote control. The unit also is capable of issuing sync clock
6 signals as an external clock.

7 The optional charger (104) is installed when the charging capability
8 needs to be boosted. The charger (104) can be connected with the internal
9 optional charger (not shown in the diagram) in respective UPS modules (10) in
10 parallel for boosting the charging current of the battery.

11 The manually operated bypass switch (102) is installed only if necessary,
12 such as in situations that all UPS modules need to be removed, by providing a
13 bypass for power supply to the load.

14 The architecture of a typical UPS module (10) is shown in Fig. 2,
15 comprising:

16 an optional input filter (not shown in the diagram) being connected to the
17 AC input;

18 an AC/DC converter (11) being connected to the output of the filter for
19 converting AC to DC;

20 a DC bus (12) being connected both to the output of the AC/DC
21 converter (11) and DC/DC converter (14);

22 a DC/AC inverter (13) being connected to the DC bus (12) ;

23 a DC/DC converter (14) being connected to the DC input, and the output
24 is connected to the DC bus (12);

1 an optional charger (15) being connected to the AC input;
2 a power supply unit (16) being connected to the DC input and the
3 optional charger providing the operating voltage for the unit;
4 a unit controller (17) being respectively connected by the DC/AC
5 inverter (13), AC/DC converter (11), and DC/DC converter (14) for controlling
6 the operation of the UPS module and for controlling the parallel operation.

7 Under the above structure, when the main line is in normal conditions,
8 the AC input is the main source of electrical power, which is then fed through the
9 AC/DC converter (11) converting from AC to DC voltage and onto the DC bus
10 (12), and further through the DC/AC inverter (13) converting DC to AC output
11 and onto the AC output bus, forming a double conversion parallel framework.

12 When the main line is failed, the power source is switched to the
13 secondary DC power, and through the DC/DC converter (14) converting to high
14 voltage DC onto the DC bus (12), and then through DC/AC inverter (13)
15 converting DC to AC output and onto the common AC output bus.

16 The power for the internal operation of the unit is mainly supplied by the
17 charger (15) and the internal battery (101) or externally connected battery (105),
18 regardless of the power source (AC or DC). This provides the power for
19 operating devices such as fans, microprocessors, and the power switches.

20 The switch (SWA) shown in the diagram refers to the AC from the
21 DC/AC inverter (13), and the switch over from AC power coming from the AC
22 input. The switching speed equals to the mode transition time. For each UPS
23 module, it first puts the AC input, DC input, and AC output connected to other
24 UPS modules (10), and then the controller (17) through the parallel control bus to

1 exchange signals with other controllers (17) in other UPS modules (10) to
2 accomplish load balancing and system stability.

3 The unit controller (17) as in one of the operational models shown in Fig.
4 3 comprises:

5 a microprocessor (171) with digital signal processor (DSP) capability,
6 and built in with multi-mode functions as shown in Figs 6-10. The controller (17)
7 further includes a general-use I/O control circuit (174), an A/D detection circuit
8 (175), an output power switch driving circuit (176), being respectively connected
9 to the AC/DC converter (11), DC/DC converter (14), charger (15) and DC/AC
10 inverter (13);

11 a photo-coupled bi-directional communication bus (172);

12 an analog signal synthesis line (173) being connected to the
13 microprocessor (171) for synthesizing the output current from UPS modules
14 (10);

15 In the present embodiment, the microprocessor (171) acts as the central
16 control unit for the UPS module (10). To accomplish load balancing, the
17 microprocessor (171) performs a range of signal detection for output voltage,
18 output current, and cross conduction current from the DC/AC inverter (13), and
19 internal computation to produce the required PWM duty cycle, and through the
20 output power switch driving circuit (176) it controls the output power switch of
21 the DC/AC inverter (13) to generate the required output voltage and current. The
22 microprocessor (171) computes the duty cycle of output power of inverter based
23 on the control data from the feedback output voltage and current and the feed
24 forward AC output current and voltage.

1 The controller (17) of the respective UPS module (10) can obtain the
2 data with respect to the total load current through the microprocessor (171), and
3 pass them to the microprocessor with impedance matching for computation of
4 the total load current.

5 The photo-coupled bi-directional communication bus (172) can be used
6 for configuring the virtual master and for transmission of sync clocks. One of the
7 operational models of the photo-coupled bi-directional communication bus is
8 shown in Fig. 4 comprising two photo-couplers, and a plurality of transistors and
9 resistors respectively connected to the input and output terminals of the
10 microprocessor (171) of the UPS module (10), such that the built-in
11 microprocessor (171) is able to perform synchronous signal transmission and
12 reception in both directions. The time delay factor in signal transmission can be
13 incorporated into the computation model, so that the microprocessor (171)
14 sending out the signal is able to receive the same message issued before. For the
15 virtual master, one of the signal wires of the photo-coupled bi-directional
16 communication bus (172) is used as a sync clock line, directly connected to the
17 input capture of the controller (17) for frequency detection, such that all UPS
18 modules (10) can be synchronized in identical phase.

19 An example of the analog signal synthesis line is shown in Fig. 5. The
20 respective UPS module can use a current transformer to extract the current
21 waveform, and the microprocessor (171) through synthesis with appropriate
22 impedance matching (Z_1 - Z_n) to produce the required power distribution signal
23 for sharing the load. The analog signal synthesis line (173) further includes a
24 switch (SW_1 - SW_n). When the system only has one UPS module operating or

1 being switched to wireless control of parallel operation, the switch (SW1-SW_n)
2 is used to disconnect the respective UPS module (10) from the parallel control
3 bus.

4 The above-mentioned parallel control bus is used for electing a virtual
5 master through the master arbitration participated by one or more parallel UPS
6 modules connected in parallel as already described in detail through Figs 6-10.

7 The present invention introduced the mixed control method, using the
8 built-in redundant control logic in each respective UPS module to perform role
9 detection, mode switching, and master arbitration. When the virtual master is
10 down or failed, other UPS modules will be able to re-elect a new virtual master
11 through the arbitration process, thus reducing the risk of single point failure.

12 The present invention design has adequately taken into consideration the
13 necessary redundancy for parallel operation. Since the virtual master is
14 dynamically elected from among all the UPS modules, the number of is equal to
15 the total number of UPS modules in the system. The redundancy factor in this
16 case should be higher than that with only a redundant units and dedicated
17 controllers such as US Pat. 6,201,319, thus decreasing the risks of a system-level
18 failure of single-point failure.

19 Furthermore, there is only one virtual master to coordinate the operation
20 of a plurality of virtual slaves, and the architecture of this invention constructs
21 simpler structure compared to the prior art US Pat.6,396,170, which system is
22 operated by dynamically selecting one UPS module to be the master dispensing
23 with the vice master. Due to the compact and robust skill in this invention, the
24 possibilities of the system-level single point failure could be decrease to as low as

1 possible. Furthermore, since there are only one virtual master and virtual slaves,
2 the so-called virtual vice-master is not necessary in this invention, such that even
3 only one module could sustain the system in normal operation. Therefore, the
4 availability and flexibility is better than the prior art US Pat, 6,396,170, which
5 both master and vice-master much exist in the system, and system could be
6 normally operated. Only one module is not possible to make the system operate
7 in the prior art. From the above mentioned characteristics, the present invention
8 provides a more effective control method for controlling parallel operation of
9 UPS modules with due consideration of redundancy, fault tolerance and
10 flexibility.

11 The present invention has constructed the system with a simple structure
12 using fully redundant UPS modules, without external control circuitry or
13 dedicated controllers, as opposed to the case of prior art which employs a
14 dedicated controller in conjunction with a redundancy intelligence management
15 (RIM) for redundant control, and in another case in prior art the inventor uses a
16 master, a vice master, peers method, and complicated-wasting-type parallel
17 resource arrangement in the system.

18 The foregoing description of the preferred embodiments of the present
19 invention is intended to be illustrative only and, under no circumstances, should
20 the scope of the present invention be so restricted.